

## Lighting Tables for Existing/Base Equipment

4/8/2010

### T12 Fluorescent Lamps and Fixtures with Electronic Ballasts

LAMP LENGTH	DESCRIPTION	NUMBER OF LAMPS	CODE	WATTS	LAMP LENGTH	DESCRIPTION	NUMBER OF LAMPS	CODE	WATTS		
2'	F20T12	1	8000	28	5'	F60T12	1	8029	100		
		2	8001	46			2	8030	135		
		3	8002	68			F60T12 HO	1	8031	126	
		4	8003	91				2	8032	170	
3'	F30T12 (30 watt lamps)	1	8004	43		3		8033	250		
		2	8005	70		4	8034	330			
		3	8006	113		F60T12 VHO	1	8035	157		
		4	8007	138			2	8036	310		
	F30T12 (25 watt lamps)	1	8008	40		6'	F72T12	1	8037	107	
		2	8009	63				2	8038	145	
		3	8010	103				F72T12 HO	1	8039	135
		4	8011	125					2	8040	195
4'	F40T12 (40 watt lamps)	1	8012	46	3		8041		265		
		2	8013	81	4		8042	330			
		3	8014	123	F72T12 VHO		1	8043	180		
		4	8015	161			2	8044	300		
	F40T12 (34 watt lamps)	1	8016	42			3	8045	450		
		2	8017	69	8'		F96T12 (75 watt lamps)	1	8046	100	
		3	8018	108				2	8047	180	
		F48T12	1	8020			55	F96T12 (60 watt lamps)	1	8048	83
2	8021		93	2		8049	123				
F48T12 HO	1	8022	76	F96T12 HO (110 watt lamps)		1	8050	139			
	2	8023	130			2	8051	257			
	3	8024	195			3	8052	330			
	4	8025	260	F96T12 HO (95 watt lamps)		1	8053	125			
F48T12 VHO	1	8026	134			2	8054	227			
	2	8027	240	F96T12 VHO (215 watt lamps)		1	8055	230			
	3	8028	450			2	8056	375			
			3			8057	570				
					F96T12 VHO (185 watt lamps)	1	8058	200			
				2		8059	325				

### Existing/Base Incandescent Lamps

LAMP WATTAGE	WATTS	CODE	LAMP WATTAGE	WATTS	CODE
6 Watt	6	8095	300 Watt	300	8066
40 Watt	40	8060	450 Watt	450	8096
50 Watt	50	8097	500 Watt	500	8067
60 Watt	60	8061	575 Watt	575	8098
75 Watt	75	8062	750 Watt	750	8068
100 Watt	100	8063	1000 Watt	1000	8069
150 Watt	150	8064	1500 Watt	1500	8070
200 Watt	200	8065			

## Lighting Tables for Existing/Base Equipment

4/8/2010

### Existing/Base T8 Lamps

DESCRIPTION	WATTS	CODE
4' - 32 Watt T8 Lamps Only (Use Codes 475 through 478 for New Equipment Code)	32	8091

### Existing/Base T5 Lamps

DESCRIPTION	WATTS	CODE
54 Watt T5 HO Lamps Only (Use Codes 2088 and 2089 for New Equipment Code)	54	8101

### Existing/Base Mercury Vapor Fixtures

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
50 Watt - 1 lamp	118	8071	400 Watt - 2 lamp	880	8075
100 Watt - 1 lamp	120	8072	500 Watt - 1 lamp	570	8077
175 Watt - 1 lamp	205	8073	700 Watt - 1 lamp	775	8078
250 Watt - 1 lamp	285	8074	1000 Watt - 1 lamp	1075	8079
400 Watt - 1 lamp	454	8076			

### Existing/Base Metal Halide Lamps

DESCRIPTION	WATTS	CODE
250 Watt Metal Halide Lamps Only (Use Code 983 or Code 984 for New Equipment Code)	250	8099
400 Watt Metal Halide Lamps Only (Use Code 985 or Code 986 for New Equipment Code)	400	8100

### Existing/Base Metal Halide Fixtures

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
150 Watt - 1 lamp	187	8086	400 Watt - 2 lamp	880	8090
175 Watt - 1 lamp	210	8087	1000 Watt - 1 lamp	1070	8092
250 Watt - 1 lamp	295	8088	1000 Watt - 2 lamp	2140	8093
400 Watt - 1 lamp	460	8089	1000 Watt - 3 lamp	3210	8094

### Existing/Base Exit Signs

DESCRIPTION	WATTS	CODE	DESCRIPTION	WATTS	CODE
15 Watt - 2 lamp Incandescent	30	8080	20 Watt - 2 lamp Incandescent	40	8081

**Definitions:**

HO - High Output

VHO - Very High Output